

# RZM 15-0900

# RZM 18-0900

## Technical Data

	Nominal motor power kW	Poles	Motor size	Motor voltage V	Phases	Nominal frequency Hz	Connection	Nominal motor current A	Nominal motor speed 1/min	Max. fan speed 1/min	Max. operating frequency Hz	Weight kg
<b>RZM 15-</b>												
0900-8D-31	11.0	8	180L	400	3~	50	△	25.0	725	790	54	706
0900-8D-33	15.0	8	200La	400	3~	50	△	32.5	725	870	60	847
0900-6W-34	22.0	6	200L	400	3~	50	△	42.5	978	985	50	847
0900-6W-37	30.0	6	225M	400	3~	50	△	57.0	980	1100	56	981
0900-6W-39	37.0	6	250M	400	3~	50	△	70.0	982	1180	60	1028
0900-6W-41	45.0	6	280S	400	3~	50	△	83.0	985	1260	63	1265
0900-6W-42	55.0	6	280M	400	3~	50	△	99.0	985	1350	68	1265
<b>RZM 18-</b>												
0900-4W-41	75.0	4	280S	400	3~	50	△	132.0	1485	1485	50	1354

**Motor code:**

- W = Asynchronous motor (efficiency class IE2)
- D = Asynchronous motor

**Dimensions** in mm, subject to change.

RZM 15-0900  
RZM 18-0900

Motor	G	k1	k2
180	2246	35	-
200	2246	35	2
225	2292	35	25
250	2376	35	39
280	2508	95	40

**Accessories**

	Frequency inverter 6SE6430-	Control Panel for frequency inverter 6SE6420- and 6SE6430-	Line Choke for 3~
<b>RZM 15-</b>			
0900-8D-31	6SE6430-2AD31-5CA0	6SE6400-0BE00-0AA0	6SE6400-3CC03-5CD3
0900-8D-33	6SE6430-2AD31-8DA0	6SE6400-0BE00-0AA0	6SE6400-3CC04-4DD0
0900-6W-34	6SE6430-2AD33-0DA0	6SE6400-0BE00-0AA0	6SE6400-3CC05-2DD0
0900-6W-37	6SE6430-2AD33-7EA0	6SE6400-0BE00-0AA0	6SE6400-3CC08-3ED0
0900-6W-39	6SE6430-2AD33-7EA0	6SE6400-0BE00-0AA0	6SE6400-3CC08-3ED0
0900-6W-41	6SE6430-2AD34-5EA0	6SE6400-0BE00-0AA0	6SE6400-3CC08-3ED0
0900-6W-42	6SE6430-2AD35-5FA0	6SE6400-0BE00-0AA0	6SE6400-3CC11-2FD0
<b>RZM 18-</b>			
0900-4W-41	6SE6430-2AD37-5FA0	6SE6400-0BE00-0AA0	6SE6400-3CC11-2FD0