

RZM 15-0560

Technical Data

RZM 15-	Nominal motor power kW	Poles	Motor size	Motor voltage V	Phases	Nominal frequency Hz	Connection	Nominal motor current A	Nominal motor speed 1/min	Max. fan speed 1/min	Max. operating frequency Hz	Weight kg
0560-4D-23	7.5	4	132Ma	400	3~	50	△	15.4	1450	1500	51	276
0560-4D-26	11.0	4	160Ma	400	3~	50	△	22.0	1460	1710	58	343
0560-4D-28	15.0	4	160L	400	3~	50	△	30.0	1460	1900	65	343
0560-4W-30	18.5	4	180M	400	3~	50	△	35.0	1465	2040	69	380
0560-4W-31	22.0	4	180L	400	3~	50	△	41.5	1465	2160	73	380
0560-4W-33	30.0	4	200L	400	3~	50	△	56.0	1470	2400	81	518

Motor code:

- W = Asynchronous motor (efficiency class IE2)
- D = Asynchronous motor

Dimensions in mm, subject to change.

RZM 15-0560

Motor	G	G1	G3	k1	k2
132	1540	497	80	15	-
160	1734	497	80	15	-
180	1734	497	80	15	-
200	1774	518	100	-	1

ZSR 51-0560 ZSG 01-0560 WBS 01-0560

ZSG 15-2727

ZKE 15-2727 130

ZKF 15-2727 715 35

RD 0 RD 90 RD 270 LG 0 LG 90 LG 270

Accessories

RZM 15-	Frequency Inverter Unit MM420 for 3~	Line Choke for 3~	Frequency inverter 6SE6430-	Control Panel for frequency inverter 6SE6420- and 6SE6430-
0560-4D-23	MM420 3AC 400V 7.50KW EMV B	6SE6400-3CC02-2CD3	-	-
0560-4D-26	MM420 3AC 400V 11.0KW EMV B	6SE6400-3CC02-5CD3	-	-
0560-4D-28	-	6SE6400-3CC03-5CD3	6SE6430-2AD31-5CA0	6SE6400-0BE00-0AA0
0560-4W-30	-	6SE6400-3CC04-4DD0	6SE6430-2AD31-8DA0	6SE6400-0BE00-0AA0
0560-4W-31	-	6SE6400-3CC04-4DD0	6SE6430-2AD32-2DA0	6SE6400-0BE00-0AA0
0560-4W-33	-	6SE6400-3CC05-2DD0	6SE6430-2AD33-0DA0	6SE6400-0BE00-0AA0